## Accessories AC Solid-core Current Transformer Type CTD-8Q (27 max 55x100 mm)

#### **CARLO GAVAZZI**



#### **Product Description**

Solid-core current trans- Rated primary current from former with bus-bar mount- 1000 to 4000A. ing facility.

#### Bus-bar type solid-core current transformer

- Accuracy class 0.5
- Current range from 1000 to 4000A
- Up to 8 bus-bar fixing screws
- Double screw terminals (up to 4-wire connections)
- Sealable terminal block covers



mouol		
Primary current —		
Secondary current -		
Option		
epaon		

#### **Type Selection**

Model	Primary current	Secondary current	Option
CTD-8Q	1000 1500 2000 2500 3000 4000	5A	XXX: none

#### **Input Specifications**

Operating frequency	50-60 Hz
Max. system voltage	0.72 kV
Rated insulation level	3 kV/1 min. @ 50 Hz
Insulation class	В
Short-time current rating I <sub>th</sub> I <sub>dyn</sub>	Typical 100 $I_n$ /1 s 2.5 $I_{th}$ The short-time thermal current $I_{th}$ is anyway limited by the cable/bus-bar size
Security factor (FS)	≤ 10

# Security factor (FS) ≤ 10 Cable Clipse General Specifications Weight

Standards	According to EN61869-2
Housing	Polycarbonate UL94 V2
Mounting	Bus-bar mounting
Standard accessories	Two terminal block screws. Eight bus-bar fixing screws. Two sealable terminal block covers.

Working temperature	-30°C to +40°C (-22°F to 104°F) (R.H. < 90% non condensing @ 40°C)
Storage temperature	-30°C to +70°C (-22°F to 158°F) (R.H. < 90% non condensing @ 40°C)
Approvals	CE
Connection Cable cross section area	Screw type From 1.5 to 4 mm <sup>2</sup>
Protection degree	IP20
Bus-bar size	Max. 55x100 mm
Weight	< 1.1 Kg

## **Output Specifications**

Rated secondary current	5 A
Burden	15 VA

Wiring Diagram



### **Dimensions (mm)**



